


NASA TECH BRIEF



NASA Tech Briefs are issued by the Technology Utilization Division to summarize specific technical innovations derived from the space program. Copies are available to the public from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia, 22151.

Transistorized Circuit Clamps Voltage With 0.1% Error



The problem: To apply two accurately clamped voltage levels (+18 or 0 volts) to the input of a digital-to-analog resistive matrix that binarily develops a deflection staircase.

The solution: A transistorized clamping circuit that clamps either of two voltage levels (+18 or 0 volts) with less than 0.1 percent voltage offset.

How it's done: When a positive 5.5-volt level is applied to the base of transistor Q_1 through resistor R_1 , transistor Q_1 is driven into saturation. In this state, the collector-emitter voltage of transistor Q_1 is

approximately 30 millivolts and is relatively independent of temperature. The output of transistor Q_1 is applied directly to the digital matrix and to the base of transistor Q_2 through resistor R_3 . This holds transistor Q_2 at cutoff, which in turn keeps transistor Q_3 (operating as an "inverted-mode" switch) biased off.

When a zero-volt level is applied to the base of transistor Q_1 through resistor R_1 , transistor Q_1 is biased off. Transistor Q_2 is driven into saturation by current from the 24.5-volt supply through resistors R_2 and R_3 . The output of transistor Q_2 turns transistor

(continued overleaf)

Q₃ on and allows the 18-volt supply to be applied through transistor Q₃ to the digital matrix. The collector-emitter voltage in transistor Q₃ is approximately 5 millivolts.

Notes:

1. Whereas ideal output levels are 18.0 volts and 0.0 volt, actual performance obtainable is 18.005 volts ± 5 mv, and 0.030 volt ± 15 mv.
2. Although the speed of operation of this clamping circuit technique is limited by the charge storage in transistor Q₁, it may be useful for analog, digital, and hybrid circuit applications.

3. Inquiries concerning this invention may be directed to:

Technology Utilization Officer
Goddard Space Flight Center
Greenbelt, Maryland, 20771
Reference: B65-10118

Patent status: NASA encourages the immediate commercial use of this invention. Inquiries about obtaining rights for its commercial use may be made to NASA, Code AGP, Washington, D.C., 20546.

Source: Radio Corporation of America,
under contract to Goddard Space Flight Center
(GSFC-196)